



**Art-Nr.: 33-BUM-Parent.2**

# BUM Messumformer für Spannung 1 VAC 85 - 265 V AC/DC

## Sizes:

Dimension (BxHxT mm): 22,5 x 110 x 78

## Technical Data:

measuring range: 1 VAC  
power supply: 85 - 265 V AC/DC

## General technical Data:

|                       |                                        |
|-----------------------|----------------------------------------|
| Dimension (BxHxT mm): | 22,5 x 110 x 78                        |
| Type-Name:            | BUM                                    |
| touch protection:     | EN 50274                               |
| ambient temperature:  | -25 - +60 °C                           |
| climatic resistance:  | according to VDE 0435T.2021            |
| mounting:             | DIN rail DIN EN 50022                  |
| accuracy class:       | 0,5%                                   |
| power consumption:    | 2 VA                                   |
| housing width:        | 22,5 mm                                |
| overload capacity:    | 50 % continuous                        |
| overload capacity:    | 200 % for 5 s                          |
| Output:               | 0/4 - 20 mA or 0/2 - 10 V (switchable) |
| Display:              | LED                                    |


## Technical images:

### ARTIKELNUMMER


33.x11.xx.yyy  
 Messbereich (min.60mV; max. 500V)  
 Versorgungsspannung : 01 - 24V AC/DC  
 02 - 230V AC  
 06 - 110V AC  
 Messart: 0 - AC ; 1 - DC

### CODIERSCHALTER

Ausgangssignal  
z. B 4-20mA



- ☐ 4-20mA
- ☐ 0-20mA
- ☐ 2-10V
- ☐ 0-10V



## Contact

Dahms GmbH Max-Keith-Straße 66 45136 Essen Telefon: 0201 - 890885-0 E-Mail: [dahms@dahms-gmbh.de](mailto:dahms@dahms-gmbh.de)